

ALLNET Medienkonverter 10BASE-T/10BASE2 auf BNC "ALL0500v3" DC 12VDC

>>> Zum Shop-Artikel



EAN CODE

The ALL0500v3 Converter provides easy and affordable solution for connecting your existing Thin Ethernet adapter card or Thinet Coax BNC Ethernet Network to a 10Base-T UTP network. The ALL0500v3 converts signals from Thin Ethernet for transmission over Unshielded Twisted-Pair (UTP) cable to a 10Base-T hub.

Ports:

1xRJ-45 from (Hub/station)
1xBNC socket to 10 Base-2

Cable lengths:

100 M max. per UTP cables
185 M max. per Thin Ethernet

Power supply:

Input 110V or 220V AC
Output 12V DC, 1 Amp

Environmental:

Temperature: 0 to 55C (standard operating)
Humidity: 10 to 90% (non-condensing)
Standards
10 to 90% (non-condensing)
Meets FCC Class A Subpart B of Part 15 Requirement
IEEE 802.3 10Base-T/10Base-2
Star CSMA/CD

Topology

Baseband Twisted Pair expand upon to 4 level Thinnet up to 30 Hubs
Dimensions: 0.79? (H) x 2.17? (W) x 4.09? (D)
CE and FCC Certification



Merkmale

Merkmal	Wert
Features:	BNC
Gewicht:	0.5 Kg
Garantie:	12.00 Monate

Klicken Sie hier um weitere Artikel aus dieser Kategorie in unserem Shop zu entdecken.